ROBE lighting s .r. o., Hazovice 2090
75661 Roznov pod Radhostem
Czech Republic

Tel: +420-571-751500
Fax: +420-571-751515
Email: info@robe.cz

DMX Control 1536™

This new and the most effective controller in Robe range comes with 3 DMX 512 outputs, which enables to control up to 1536 DMX channels or 48 fixtures of up to 32 channels each. A show can be created from up to 4752 scenes, consisting of presets and chases. The range of 1152 shows, presets and/or chases can be recorded into 32 pages. The design was created with 48 Multi Function Quick access buttons. Flash memory is used, which allows software updates via compact flash card.

ROBE lighting s .r. o., Hazovice 2090
75661 Roznov pod Radhostem
Czech Republic

Tel: +420-571-751500
Fax: +420-571-751515
Email: info@robe.cz

Technische Spezifikation

Elektrische Spezifikationen

- Power supply: 115/230 V, 50/60 Hz
-
- Voltage selection switch

Mechanische Spezifikationen

- Height: 178 mm (7.0″)
-
- Width: 584 mm (23.0″)
- Length: 711 mm (28.0″)
- Weight: 17 kg (37 lbs)

Steuerung und Programmierung

- Control 48 moving light fixtures up to 32 channels each
-
- 1536 DMX Channels
- 4752 programmable scenes
- 1152 programmable chases
- 1152 programmable shows
- 1152 programmable presets
- 48 fixture groups
- 3 DMX Universe
- Fade times up to 90 minutes
- Run 16 chases simultaneously
- Run 17 shows simultaneously
- Playback scenes using buttons or playback faders
- Effect generator to create chase effects.
- Factory ready color, gobo, focus & effect presets
- Large moving light fixture library available
- Scene preview with “Go” button
- Solo feature allows scenes to track through or play solo
- Scenes can be combined and recorded as new scenes
- Scenes, shows, chases and presets can be assigned to the playbacks.
- Playbacks can manually fade channels (LTP mode) or trigger timed fades while manually controlling dimmer levels (HTP mode)
- 80 Character backlit display for easy programming
- 4 menu and control data wheels
- 48 Multi function Quick access buttons
- 8 dedicated playback faders with 32 pages
- 8 flex faders with page selection for moving light channels, conventional dimmers or additional playbacks.
- Pan/tilt joystick with coarse/fine control
- Grand master fader
- Flex master fader
- Go, stop and back buttons
- Blackout, audio and beat buttons

ROBE lighting s .r. o., Hazovice 2090
75661 Roznov pod Radhostem
Czech Republic

Tel: +420-571-751500
Fax: +420-571-751515
Email: info@robe.cz

Verbindung

- 3x 3-Pin DMX Outputs
-
- 3x 5-Pin DMX Outputs
- Midi-In port
- CF-drive for memory back up, loading fixture profiles and software updates
- PS2 Keyboard input
- RS-232 Port, for PC interface
- RCA Audio input for Chases
- 2x USB LITE connectors (for gooseneck lamp)